

SERVICE
2510F TELEPHONE SETS

1. GENERAL


1.01 Reissued to show(s) strap removed when C4A ringer is used.

TABLE A
POLARITY GUARD CONNECTIONS
(P-90D052 GUARD ASSEMBLY)

LEAD	COLOR	REMOVE FROM	CONNECT TO	
		NET.	POLARITY GUARD	NET.
Dial	BK	RR	T	
Line Switch	BR	C	S	
Polarity Guard	W			C
	G			RR

Note: For use when specified by local instructions for end-to-end signaling installations.

11



NOTES:

- ON SETS EQUIPPED WITH A 425G NETWORK, THE LEADS SHOWN CONNECTED TO THE S AND T TERMINALS SHOULD BE CONNECTED TO TERMINALS 9 AND 10 RESPECTIVELY ON THE TERM. STRIP.
- CONNECTIONS SHOWN ARE FOR RINGING ON LINE 1. TO RING ON LINE 2, MOVE (S) STRAP LEAD AND (BK) RINGER LEAD TO TERMINALS 3 AND 4 RESPECTIVELY.
- TO SILENCE RINGER PERMANENTLY CONNECT (BK) RINGER LEAD TO K OF NETWORK.
- SETS ARE FACTORY WIRED TO PROVIDED BRIDGED RINGING. CONNECTIONS FOR C4B RINGER SHOWN. IF C4A RINGER IS USED WIRE AS FOLLOWS:
(BK) TO 2 OF TERM. STRIP (S-R) TO A OF NETWORK (S) TO K OF NETWORK (R) TO 1 OF TERM. STRIP. REMOVE (S) STRAP FROM A OF NETWORK AND 1 OF TERM. STRIP.
- LINE SWITCH SEQUENCE, HANDSET REMOVED:
bc - MAKES ab - BREAKS
de - MAKES fg - BREAKS

TPA 542445

◆ Fig. 1—2510F Telephone Set Connections, 2-Line Pickup and Signaling ◆