SERVICE

565HK AND 565HKM TELEPHONE SETS

1. GENERAL

1.01 This section provides connection information for the 565HK (MD) and 565HKM telephone sets (Fig. 1).

1.02 Reissued to:

- Change 2.09 to include lead colors
- Change Note 4, Fig. 1 and 2 to include lead colors.
- 1.03 The 565HKM modular telephone set is similar to the 565HK except the modular G15A handset with its associated H4DU handset cord and 616D jack assembly is used in place of the hard-wired G3A-type handset and cord.

2. CONNECTIONS

- 2.01 These sets are factory-wired for use with 1A1 or 1A2 KTS, 3-type or 4A speakerphone, and individual or common line ringer (Fig. 1 and 2).
- 2.02 When used with 1A KTS and optional features, modify set wiring as shown in Fig. 3 or 4.
- 2.03 The hold key position can be illuminated, but 51A lamp is not furnished with set and must be ordered separately.
- 2.04 All convertible key positions are supplied as pickup keys. To convert from pickup (locking) to signaling (nonlocking), remove the 811218924 (P-12A892) screw detail from key positions

involved. Make necessary wiring change as shown in Table A.

- 2.05 Early model 565HK sets were furnished from the factory with H1A (MD) ringer, current models have H1B ringer.
- 2.06 The sets are factory-equipped with a KS-20419L1 (10 volt ac only) buzzer.
- 2.07 A 812559623 (P-25E962) auxiliary terminal strip (ordered separately) is available for auxiliary services such as buzzers, lamps, etc.
- 2.08 A D-179935 Kit of Parts (ordered separately)
 can be installed in the set when the exclusion
 feature is required. Connections are made in
 accordance with Table B.
- 2.09 When a 565HK or 565HKM telephone set is not used as a speakerphone set and is multipled with any other set furnishing speakerphone feature, speakerphone leads must be disconnected, insulated and stored either at the telephone set or at the multipling point. If not disconnected, the speakerphone leads will provide a common path between the circuits of the multipled telephone sets. The leads to be removed are as follows: T1 (V-G), R1 (G-V), P3 (V-BR), P4 (BR-V), AG (V-S), and LK (S-V). Speakerphone connections are shown in Division 512.4
- 2.10 Installation of optional items such as exclusion, auxiliary terminal strips, etc., and maintenance information common to 6-button sets can be found in Section 502-500-120.

NOTICE

Not for use or disclosure outside the Bell System except under written agreement

♦TABLE A♦

PICKUP-SIGNAL KEY CONVERSION

KEY TEL SET	CONVERTIBLE KEY OPTIONS	KEY LEADS				
		BR	Y-BR	S-R	BR-BK	
565HK and 565HKM	НРРРРР	M	M	M	X	
	HPPPPS	M	M	M	SG	
	HPPPSS	M	M	SG	Х	
	HPPSSS	X	M	SG	X	
	HPPP*P*S*	X	M	5H	N	
	HPP*P*P*S*	х	х	5H	N	

^{*} These pickup key options are used on private or intercommunicating lines with the signal key common to each line.

♦TABLE B♦

EXCLUSION SWITCH CONNECTIONS

EXCLUSION	KEY TEL	EXCLUSION SWITCH LEADS							
	SYS	BL-W	W-BL	O-W	W-O	BL-V	V-BL	0-V	V-0
On any line	1A	R*	Т*	1B†	Н*	ER	ET	EB	ЕН
	1A1 or 1A2	R*	T*	EB	H*	ER	ET	EB	EH

^{*} Terminal of line to be excluded.

[†]When other than line 1 is excluded on 1A KTS, disconnect, insulate, and store O-W mounting cord conductor from terminal 1B; connect balance lead conductor from line involved to 1B.




Fig. 1—♦565HK (MD) Telephone Set, Connections





Fig. 2—₱565HKM Telephone Set, Connections♥




NOTES:


- I. USE "B" BATTERY SUPPLY FROM KTS IF AVAILABLE. DO NOT USE 10V AC LAMP BATTERY FOR BUSY LAMP.
- FOR IA KTS WITHOUT BUSY LAMP, INSULATE AND STORE (Y-BR) D50N MTG CORD LEAD,

- † NETWORK TERMINALS-UNDESIGNATED TERMINALS ARE ON KEY TERMINAL BOARD
- # 3-TYPE SPEAKERPHONE LEAD
- H-HOLD KEY
- LS-LINE SWITCH

Fig. 3—Optional Features with 3-Type Speakerphone




A. IAI-IA2 KTS WIRED FOR BUSY LAMP WITH MIGC OR H CORD TERMINATED IN TEL SET



B. IAI-IA2 KTS WIRED FOR BUSY LAMP WITH MIGC OR H CORD TERMINATED AT 66-TYPE CONN BLK

Fig. 4—Optional Features with 4A Speakerphone (Sheet 1 of 3)



A. IA KTS WIRED FOR BUSY LAMP WITH MIGC OR H CORD TERMINATED IN TEL SET






Fig. 4—Optional Features with 4A Speakerphone (Sheet 2 of 3)





B. IAI-IAZ KTS WIRED FOR BUSY LAMP AND I HOLD WITH MIGC OR H CORD TERMINATED AT 66-TYPE CONN BLK

Fig. 4—Optional Features with 4A Speakerphone (Sheet 3 of 3)